

APPENDIX G, MAILBOX PACKAGE

Version 002 (29/10-2019)

Final

Mailbox Package

These changes take effect 13th January 2020 and cannot be implemented before. Please update as soon as possible from the 13th of January.

Packages in the mailbox is a letter with maximum weight 2 kg. **One file (same date as pickup) must be transferred in agreement with Bring per day.** EDI can be processed continuously during the day.

Mailbox package is only valid from Norway to Norway. Mailbox package must have a harmonized label, which has an EDI barcode. Barcode will be read when received at terminal and delivered at the mailbox. If the customer wants more tracking they need to use an RFID tag.

Product codes:

| Code | Name | RFID |
|-------|--|------|
| 3570 | Pakke i postkassen med sporing (traceable) Pakke i postkassen med RFID | Yes |
| 3584 | Pakke i postkassen uten sporing (non traceable) Pakke i postkassen | No |
| 9650* | Retur Pakke i postkassen | No |

Value added services:

3570 and 3584 is valid with 1081 Forenklet utlevering (Simplified delivery). See label description as well.

9650 is valid with 1073 Pickup at the mailbox. Specific dates are not possible for the pickup. Bring will do the pickup at the nearest possible date from receiving the pickup request.




Tracking overview:

| Service | EDI received | Sort at Terminal 1 | Received at terminal 2 | Loaded for Distribution | Notifications to receiver | Delivered |
|---------|--------------|--------------------|------------------------|-------------------------|---------------------------|-----------|
| 3570 | T | S | G | 3 | X12 | I4 |
| 3584 | T | S | | | | I |

- if the package, letter is too big for the mailbox it will be sent to nearest pickup point. Post i Butikk. The receiver will get notification.
- 9650 Retur Pakke I postkassen will have EDI received (T), Sort at terminal (S).

Label

See label description. <https://developer.bring.com/edi/>

| | | |
|--|--|---|
| FROM | 00001234567 Company Address 1 Address 2 Postal code/place |  |
| TO | Receiver Address 1 Address 2 Postal code Town/Place ☎ 999 99 999 | |
|  | | |
|  *LA003755076N0* | | |

Special requirements EDI

Sender address (NAD+CZ) and receiver address (NAD+CN) must be Norwegian addresses.

EDI data must contain following *additional* data:

- **RFF+CU:** Bring Mail Nordic customer only. **Bring Mail Nordic/Mandatory.** Reference, order-number is given by the sales contact in Bring for Bring Mail Nordic customers. **Other customers/Optional.** Non Bring Mail Nordic customers can use this as today.
- ~~RFF+AEP: Agreement number for Posten Norway. Bring Mail Nordic/Mandatory. Other customers/Optional.~~
- ~~NAD+CZ segment in connection with COM segment and e-mail address. Bring Mail Nordic/Mandatory support@bringmail.eu. Other customers/Mandatory Freight document e-mail address.~~
- ~~FTX+SSR segment with service code 1091 is mandatory.~~
- Eadvising 1091 is no longer required as long as email and/or mobile is in the file.

File example:

UNA:+.? '
UNB+UNOC:3+SE556677889901:30+7080003248381:14+161201:1500+2017'
UNH+1+IFTMIN:D:04A:UN:BIG14'
BGM+610++5'
DTM+137:201612011500:203'
FTX+PRD+++3584'
CNT+7:1.0:KGM'
CNT+11:1:PCE'
RFF+SRN:LA006260542NO'
RFF+CU:Customer name'
TDT+20+++3++BPN::87'
NAD+CZ+10999337289::87++Customer Name+Postboks 1800+Oslo++0061+NO'
NAD+CN+++Veronica Mickelsen+Gardsstølsvegen 1+Førde++6812+NO'
CTA+IC'
COM+97772924:AL'
COM+veronica.mickelsen@hotmail.com:EM'
NAD+ZRR+++Return address C/O Responsservice+Postboks 01+Oslo++2711+NO'
NAD+FP+10009337281::87'
NAD+NI+++Veronica Mickelsen+Gardsstølsvegen 1+Førde++6812+NO'
GID+1+1:CT'
FTX+AAA+4+++Textiles'
MEA+WT+G+KGM:1.0'
PCI+18+LA006260542NO'
UNT+25+1'
UNZ+1+2017'