

APPENDIX G, Home Mailbox Parcel

Version 004 (26/06-2025)





Home Mailbox Parcel

Home Mailbox Parcel is a letter with maximum weight 5 kg.

Home Mailbox Parcel is only valid from Norway to Norway. Home Mailbox Parcel must have a harmonized label, which has an EDI barcode. Barcode will be read when received at terminal and delivered at the mailbox. If the customer wants more tracking they need to use an RFID tag.

Product codes:

Code	Name	RFID
3570	Pakke hjem i postkassen RFID	Yes
3584	Pakke hjem i postkassen	No

Value added services:

3570 and 3584 is valid with additional services:

- 1081 Forenklet utlevering (Simplified delivery)
- 1280 Reservasjon mot endring (Reservation against change)
 - If the Home Mailbox Parcel (3570 and 3584) is too big for the mailbox it will be sent to nearest manned pickup point.
 - If 1081 is activated from sender/receiver then we will deliver outside the door.
 - If 1280 is activated from sender then we will deliver to nearest manned pickup point.

Label

See label description. https://developer.bring.com/edi/transport-label-specifications/





Special requirements EDI

Sender address (NAD+CZ) and receiver address (NAD+CN) must be Norwegian addresses.

```
File example:
```

UNA:+.? ' UNB+UNOC:3+556677889901:30+7080003248381:14+240401:1500+2017' UNH+1+IFTMIN:D:04A:UN:BIG14' BGM+730++9' DTM+137:202404011500:203' FTX+PRD+++3584' FTX+SSR+++1280' CNT+7:1.0:KGM' CNT+11:1:PCE' RFF+CU:123456789' TDT+20++++NPB::87' NAD+CZ+10999337289::87++Customer Name+Testveien 4+Oslo++0061+NO' NAD+CN+++Sylvester Shyster+Gardsstølsvegen 110+Førde++6812+NO' CTA+IC' COM+99999999:AL' COM+Gus.Goose@somewhere.com:EM' NAD+ZRR+++Customer C/O Practical Gadget+Postboks 11+Oslo++1201+NO' NAD+FP+10999337289::87' GID+1+1:CT' FTX+AAA+4++Textiles' MEA+WT+G+KGM:1.0' PCI+18+LB006260542NO' UNT+21+1' UNZ+1+2017'